
DUAL OUTPUT PROCESS SIGNAL SPLITTER



- Process signal replication.
- One input two galvanically isolated outputs.
- Four way isolation input isolation > 1000 VDC between input, outputs and auxiliary supply.
- □ Various input and output options 0-20 mA, 4-20 mA, 0-10 V DC, or ±10V (others on request).
- Dual relay or digital outputs for alarms optional.
- Each output can be different if required.
- Microprocessor based with two digital inputs and two digital (or relay) outputs for customized applications.

Also adapted for:
Peak Valley Hold Unit,
Process Signal Range
Splitter

PART NUMBERING:



a = I: current b = A: 4 to 20 mA B: 0 to 20 mA D: 0 to 1 mA E: 0 to 5 mA

a = V: voltage b = A: 0 to 10 V B: 0 to 50 mV (input only) C: ±50 mV (input only) D: 0 to 5 V

D: 0 to 5 V E: ±5 V F: 1 to 5 V G: ±10 V

APPLICATIONS:

Providing isolated process signal replication.

Parallel redundant systems using a single transmitter.

Adding two isolated outputs with minimal effect on the existing process loop.

Alarm trip unit with dual relay or digital outputs.

□ One input with various options -

Current (DC): 4-20 mA, 0-20 mA, (factory installed options are 0-1 A, 0-5 A and 0-10 A). Loop power available at +15 V, 22 mA for loop

powered transmitter inputs. **Voltage (DC)**: 0-100 mV, 0-1 V, 0-10 V, 0-30 V, 0-100 V and ±10 V.

Resistance: $0-100 \Omega$, $0-1 k\Omega$, $0-10 k\Omega$.

□ Two outputs with various options Current (DC): 4-20 mA, 0-20 mA.
Voltage (DC): 0-100 mV, 0-1 V, 0-10 V, ±10 V.

- Relay Outputs optional: Two alarm relay outputs 30 VDC at 1 A / 125 VAC, 0.3 A.
- Digital Outputs optional: Two opto isolated transistor outputs up to 50 V at 40 mA maximum.
- Digital Inputs optional: Two opto isolated digital inputs 30 V maximum at 5 mA.
- 24 VDC (-5%, +10%) auxiliary power supply at approximately 100 mA.

- Galvanic isolation between auxiliary supply, input and all outputs > 1000 VDC.
- □ Input impedance > 100 kΩ for voltage input versions, 50 Ω for current inputs.
- $\ \square$ Maximum load resistance 400 Ω for current outputs.
- Voltage output current maximum is 5 mA.
- Input and outputs ±10% over and under range.
- □ Step response < 100 mSec on all outputs.
- Trimpot adjustment of zero and span for each output.
- Power On/Status green LED.
- Input Status and Alarm LEDs.
- □ Operating temperature -10°C to +70°C.
- Plug-in screw terminals.
- High quality, self-extinguishing polyamide enclosure.
- DIN rail mounting enclosure 22.5 x 100 x 113 mm (width x length top to bottom x height off DIN rail).
- Approximate weight 100 g.



danntech cc

Reg. No. CK86/15338/23 Tel: +27 (0)11 792-1239 Fax: +27 (0)11 792-4687 P O Box 1023, Fontainebleau, 2032 Republic of South Africa

www.danntech.com www.danntech.co.za

danntech Itd

Co. No. 6510211 Tel: +44 (0) 75 9069 1824 15 College Close, Hamble-le-Rice Southampton, Hampshire, SO31 4QU United Kingdom www.uk.danntech.com